

# AHU-DC

Control Relay Module 24V DC

## Description



Intelligent addressable input/output module loop powered. A single volt free relay with N/O and N/C change over contacts that can be driven via the fire alarm loop. Commonly used for overriding equipment such as AHU's, Lift auto dialer, BMS and etc. The input can be linked through a volt free contact switch output of ancillary equipment reporting to the fire alarm controller. According to the pre-inputted cause and effects interface programming, the alarm controller sends out a start command to the equipment required to start. After receiving the command, the module activates its relay to change state. Once the equipment under control has operated a confirmation signal can be sent back to the fire alarm controller.

## FEATURES

Improve design for ease of wiring meaning faster installation  
Contains controllable isolator  
Earth fault monitoring

## TECHNICAL SPECIFICATIONS

Input Voltage	24V DC
Operating Temperature	0~55 °C
Output & N/C Input	Green LED
Output with feedback	Red LED
Fail Safe output with feedback	Green LED
Dimensions: L*W*H	132*89*51 (size are in mm)
Weight	370 gm.